


Cunningham RADIO TUBES

CX-220

POWER AMPLIFIER



The '20 is a three-electrode, high-vacuum, power amplifier tube designed for operation from dry-cells. It is intended for use in the last audio stage of dry-battery-operated receivers using the '99 and/or '22.

CHARACTERISTICS

| | | |
|----------------------------------|-------------|--------------|
| FILAMENT VOLTAGE (D. C.)..... | 3.0-3.3 | Volts |
| FILAMENT CURRENT | 0.125-0.132 | Ampere |
| PLATE VOLTAGE | 90 135 max. | Volts |
| GRID VOLTAGE | -16.5 -22.5 | Volts |
| PLATE CURRENT | 3.0 6.5 | Milliamperes |
| PLATE RESISTANCE | 8000 6300 | Ohms |
| AMPLIFICATION FACTOR | 3.3 3.3 | |
| MUTUAL CONDUCTANCE | 415 525 | Micromhos |
| LOAD RESISTANCE | 9600 6500 | Ohms |
| UNDISTORTED POWER OUTPUT | 45 110 | Milliwatts |
| GRID-PLATE CAPACITANCE | 4.1 | μf. |
| GRID-FILAMENT CAPACITANCE | 2.0 | μf. |
| PLATE-FILAMENT CAPACITANCE | 2.3 | μf. |
| MAXIMUM OVERALL LENGTH | | 4 1/8" |
| MAXIMUM DIAMETER | | 1 3/16" |
| BULB (See page 42, Fig. 1) | | T-8 |
| BASE | | Small 4-Pin |

INSTALLATION

The base pins of the '20 fit the standard four-contact socket. The socket should be installed to operate the tube in a vertical position. For socket connections, see page 39, Fig. 1.

The filament in this tube is designed for operation with three No. 6 dry-cells connected in series. In multi-tube receivers the use of six or nine No. 6 dry-cells connected in series-parallel to give 4.5 volts will decrease the current drain per cell and give a more stable source of filament power. If storage battery operation is preferred, a four-volt storage battery may be used. In any case, a filament rheostat should be provided to maintain the voltage applied to the filament within the stated range.

APPLICATION

For power amplifier service, the '20 will give greatest power output when operated at a plate voltage of 135 volts and the corresponding grid bias of -22.5 volts. At 90 volts on the plate and with a corresponding grid bias of -16.5 volts, good quality of reproduction may be obtained at a lower level of power output.

In receivers employing tubes of the 3.3 volt filament type, the use of the '20 in the output stage will be found desirable.